



ATTO Technology, Inc.

CacheAssure™

Getting Started Guide

Thank you for purchasing ATTO CacheAssure for your ATTO 6Gb ESAS RAID Adapter. This guide gives you the basics for installing your CacheAssure components onto your 6Gb RAID card and into your host computer system. For more information, refer to the ATTO ExpressSAS Host and RAID Adapter manual.

Note: If you are purchasing this CacheAssure™ module as part of a kit with an ExpressSAS RAID adapter included, it has been disassembled for shipment. During quality testing, the super capacitor was cycled to verify its functionality. Since a small, residual charge may remain in the super capacitor for a period of time, the assembly was removed from the RAID adapter to protect the adapter from electro-static discharge (ESD). The instructions below describe the steps to re-assemble your RAID adapter with CacheAssure.

Examine the contents of your CacheAssure packing box. If any of the items listed below are missing, contact your ATTO representative.

- 0244-FINL-000 Non-Volatile (NV) Memory Card
- SPAK-0000-BLK Power Module
- MISC-0143-R00 Industrial strength adhesive
- HDWS-0205-R45 Standoff mounting screws

1 Install Non-Volatile Memory




WARNING

ATTO CacheAssure and Host Adapters contain components that are sensitive to electrostatic discharge (ESD). ESD can cause damage to the ATTO ExpressSAS host adapter. Please follow standard methods to avoid ESD.

- 1.1 Power down the computer and unplug the computer from all power sources.
- 1.2 Open the case.
- 1.3 If your adapter is installed into the workstation, gently remove your ATTO 6Gb SAS Adapter from the PCI Express expansion slot. If you have questions about how to remove an expansion card from your system, consult your computer's documentation.


- 1.4 Remove the Power Module and NV Memory Card from the electrostatic safe packaging.
- 1.5 Plug the Power Module power cord into the Non-Volatile Module (on the RAID adapter). The plug is keyed so that it can only be plugged in one way. Please make sure that the plug is fully inserted.
- 1.6 Holding the RAID adapter firmly, plug the NV Memory Card into the RAID Host Adapter with ATTO logos in matching direction and the standoff mounts closer to the adapter's bracket.




CAUTION

Make sure the NV Memory Card is evenly aligned on both sides. If the card is placed incorrectly, damage to the Memory or Host Adapter Card may occur. This may void your warranty.

- 1.7 Make sure the NV Memory Card is firmly seated by gently pushing the card down onto the ATTO RAID Adapter, as shown:



- 1.8 Turn the Host Adapter over so that you can see the back of the printed circuit board. Use the supplied screws to secure the NV Memory Card onto your RAID adapter.



- 1.9 Use an ESD-safe crosshead screwdriver to secure the screws.

2 Install Power Module

It is the user's preference to install the Power Module while the ATTO Host Adapter is outside of the computer, or install the Power Module while the Host Adapter is seated in its PCI Express slot. If you have questions about how to remove an expansion card from your system, consult your computer's documentation. In these directions, we will assume the card is seated in its PCI Express slot.

- 2.1 Select an area for placement of the Power Module inside of the computer. Make sure it can be mounted securely and that the Power Module's power cord can reach the Host Adapter, specifically the NV Memory Card's power jack.
- 2.2 Use the heavy-duty, industrial adhesive to mount the module. Remove one side of the paper backing and apply it to the Power Module.



- 2.3 Remove and expose the other side of the adhesive.
- 2.4 Mount the Power Module into the computer.



- 2.5 Close your computer case.
- 2.6 You may power on your system.

Be careful handling the Power Module after it has been installed and powered. It may be live with power. If the board is mishandled while it is attached it may be shorted and damaged.

ATTO Technology, Inc.
155 CrossPoint Parkway
Amherst, New York 14068 USA

www.attotech.com

Tel (716) 691-1999
Fax (716) 691-9353

Sales support: sls@attotech.com
Technical support: Please visit <https://www.attotech.com/support/> for hours of operation.
techsupp@attotech.com (716) 691-1999 x242

© 2015 ATTO Technology, Inc. All rights reserved. All brand or product names are trademarks of their respective holders. No part of this document may be reproduced in any form or by any means without the express written permission of ATTO Technology, Inc.